



## PLC-5804H1/PR-4K

04 Channel NVR



### **Pollo Pty Ltd.**

Address: Suite 401, 55 Phillips St. Parramatta, NSW 2150

Phone: 1300 6600 368


Email: [info@pollo.net.au](mailto:info@pollo.net.au)

Website: [www.pollo.net.au](http://www.pollo.net.au)



## PLC-5804H1/PR-4K

### 04 Channel NVR



### Specifications:

<b>Model</b>	<b>PLC-5804H1/PR</b>
<b>Resolution</b>	8MP, 5MP, 3MP ,2MP (1080P),1.3MP (960P),1.0MP (720P)
<b>Bandwidth Inputs</b>	50Mbps
<b>Bandwidth out</b>	48Mbps
<b>Installation wizard</b>	Yes
<b>Compression</b>	Audio: G.711a Video: H.264/H.265
<b>Frame rate</b>	4K:30fps 4MP:60fps 2MP:120fps
<b>AI</b>	Yes
<b>Event</b>	MD (Sensitivity Level 1~8), Video loss, Beep, Email, Push notification to Mobile APP
<b>Playback function</b>	Fast forward / backward (2x, 4x, 8x,16x) Slow forward (1/2x, 1/4x, 1/8x,1/16x)
<b>Playback</b>	Max 4CH playback
<b>Fisheye</b>	Use WEB CMS, device does not support
<b>Local</b>	UI5.0
<b>UI WEB</b>	IE10/11 Safari V12.1 above Firefox V.52 above Google chrome V.57 above Edge V.79 above
<b>Mobile viewer</b>	Pollo Connect
<b>Push Notification</b>	TUTK/RS
<b>P/W Reset</b>	Factory Reset: Press 10 seconds
<b>VGA</b>	1 (1024*768, 1280*720, 1280*1024, 1440*900, 1920*1080 )
<b>HDMI</b>	1 (1024*768, 1280*720, 1280*1024, 1440*900, 1920*1080, 2560*1440, 3840*2160/EDID)
<b>POE</b>	NO
<b>Ethernet</b>	1 RJ45 10/100 Base-T
<b>USB</b>	USB2.0*1(front) USB2.0*1+(rear)
<b>Audio out</b>	1
<b>HDD</b>	1 SATA HDD, up to 8TB
<b>RS485</b>	NO
<b>Alarm Input/out</b>	NO
<b>Dimension (WxDxH)</b>	300X227X53mm
<b>Input Voltage/Current</b>	DC12V/2A
<b>Temperature/Humidity</b>	Temperature: 0°C~+40°C (32°F ~ 104°F) Humidity: Less than 90%RH