



## EXIT BUTTON PLL-E100



### **Pollo Pty Ltd.**

Address: Suite 401, 55 Phillips St. Parramatta, NSW 2150

Phone: 1300 6600 368

Email: [info@pollo.net.au](mailto:info@pollo.net.au)

Website: [www.pollo.net.au](http://www.pollo.net.au)



## EXIT BUTTON

### PLL-E100

#### Main Features



Particulars	Specifications
Operation Type	Mechanical Trigger
Protection Level	IP65
Max. Current	3 A
Max. Voltage	DC 36 V

## Specifications

<b>Model</b>	<b>PLL-E100</b>
<b>Size</b>	86 mm (L) x 86 mm (W) x 20 mm (H)
<b>Standard Structure</b>	Aluminum Panel, Steel Button
<b>Working Current</b>	3 A @ 36 V DC Max.
<b>Signal Output</b>	No/COM
<b>Mechanical Life</b>	500000 Tested
<b>Door Type Applicable</b>	Hollow frame and Embedded Electric Case
<b>Weight</b>	0.1 kg